


Change Wireless Password

Open up your Internet Browser (Internet Explorer, Fire Fox, Google Chrome, Apple Safari) and type the modems default IP Address in the address bar as shown below

Thomson Modem: **192.168.1.254**

You will be prompt for the modem's username and password, enter admin for both username and password




Note: By default, Telecom Cook Islands sets modem administrator username and password to admin. If username and password is incorrect, reset modem back to default settings and use Broadband Self Install Guide (Thomson) to setup the modem for broadband use


Reset modem: Push and hold the small button inside a small hole next to the power for 12 seconds. When the power LED should turn RED release the reset bottom and wait for 2 minutes before following the Self install Guide to setup your modem for broadband connection

When successful, the Home Page for the Thomson modem should display as follow


Click on Home Network




Click on **WLAN: Thomson**



The following page will show you an overview of the wireless settings
At the top right corner, click on **Configure**



Now enter the new Network Name and new wireless password (WPA-PSK Encryption Key)



Note: The network name can be anything. Wireless password is case sensitive and must be from 8 - 32 characters long

Double check wireless details before continuing in the following page and make note of your new wireless password

The screenshot shows the Thomson Gateway v7 configuration page for the WLAN interface. The page title is "Wireless Access Point - HOME_WIRELESS". It contains two main sections: "Configuration" and "Security".

Configuration:

- Interface Enabled: Yes
- Physical Address: 00:24:17:8D:F3:73
- Network Name (SSID): HOME_WIRELESS
- Interface Type: 802.11b/g
- Actual Speed: 54 Mbps
- Bands: 2.4G Hz
- Channel Selection: Auto
- Region: Europe
- Channel: 6
- Allow multicast from Broadband Network: Yes

Security:

- Broadcast Network Name: Yes
- Allow New Devices: New stations are allowed (auto)
- Security Mode: WPA-PSK
- WPA-PSK Preshared Key: NeWp4ssWORD
- WPA-PSK Encryption: TKIP+AES
- WPA-PSK Version: WPA-WPA2

Callouts in blue speech bubbles point to "HOME_WIRELESS" and "NeWp4ssWORD".

Restart Thomson Router to keep wireless settings

The screenshot shows the Thomson Gateway v7 status page. The page title is "Thomson Gateway". It contains two main sections: "Information" and "Configuration".

Information:


- Product Name: TG585 v7
- Serial Number: CP0922SF18K
- Software Release: 7.4.4.7

Configuration:


- Service Name: Routed PPP (modified by user)
- Time Since Power-on: 0 days, 0:01:50

Callouts in blue speech bubbles point to "Thomson Gateway" and "Restart".


Click the **Yes, restart my Thomson Gateway** to confirm to restart the modem



The following page will display while the modem is restarting, this usually takes about 2 minutes



When the loading bar fills to the end the modem would have finished restarting and it will display the main Thomson page



When your modem has restarted try connecting to the modem by searching for the new wireless network name

When trying to connect to the network you will be prompted for a password, enter the new password entered configured

Note: As mentioned earlier the wireless password is case sensitive and must exactly be the same as it was configured in the modem